

## OSFP-800GB-2XDR4P-C

MSA and TAA 800GBase-2xDR4+ PAM4 OSFP Transceiver (SMF, 1310nm, 2km, 2xMPO, DOM, CMIS 5.0)

### Features:

- Compliant with OSFP MSA Specifications
- Compliant with IEEE 802.3cu-2021: 8x100GBASE-FR1
- Optical Interface
- Compliant with IEEE 802.3ck-2022: 8x100GAUI-1 C2M
- Electrical Interface
- Compliant with CMIS 5.0
- 2-Wire Serial Interface with Digital Diagnostic Monitoring
- Operating Temperature: 0 to 70 Celsius
- Class 1 Laser
- RoHS Compliant and Lead-Free



### Applications:

- 8x100GBase Ethernet
- 2x400GBase Ethernet

### Product Description

This MSA compliant OSFP transceiver provides 800GBase-2xDR4+ throughput up to 2km over single-mode fiber (SMF) PAM4 using a wavelength of 1310nm via a 2xMPO connector. It can operate at temperatures between 0 and 70C. All of our transceivers are built to comply with Multi-Source Agreement (MSA) standards and are uniquely serialized and tested for data-traffic and application to ensure seamless network integration. Additional product features include Digital Optical Monitoring (DOM) support which allows access to real-time operating parameters. This transceiver is Trade Agreements Act (TAA) compliant. We stand behind the quality of our products and proudly offer a limited lifetime warranty.

ProLabs' transceivers are RoHS compliant and lead-free.

TAA refers to the Trade Agreements Act (19 U.S.C. & 2501-2581), which is intended to foster fair and open international trade. TAA requires that the U.S. Government may acquire only "U.S.-made or designated country end products.")



## Absolute Maximum Ratings

Parameter	Symbol	Min.	Typ.	Max.	Unit	Notes
Storage Temperature	T <sub>stg</sub>	-40		85	°C	
Operating Case Temperature	T <sub>c</sub>	0		70	°C	
Power Supply Voltage	V <sub>cc</sub>	-0.5		3.6	V	
Relative Humidity (Non-Condensing)	RH	5		95	%	
Data Input Voltage Differential	V <sub>DIP</sub> -V <sub>DIN</sub>			1	V	
Control Input Voltage	V <sub>I</sub>	-0.3		V <sub>cc</sub> +0.5	V	
Control Output Current	I <sub>o</sub>	-20		20	mA	
Signaling Speed Per Lane	DRL		53.125		GBd	
Operating Distance		2		2000	m	

## Electrical Characteristics

Parameter	Symbol	Min.	Typ.	Max.	Unit	Notes
Power Supply Voltage	V <sub>cc</sub>	3.135	3.3	3.465	V	
Instantaneous Peak Current at Hot Plug	I <sub>cc_IP</sub>			6600	mA	
Sustained Peak Current at Hot Plug	I <sub>cc_SP</sub>			5494.5	mA	
Maximum Power Dissipation	PD			16.5	W	
Maximum Power Dissipation (Low-Power Mode)	PD <sub>LP</sub>			2	W	
Control Input Voltage - High	V <sub>IH</sub>	V <sub>cc</sub> *0.7		V <sub>cc</sub> +0.3	V	
Control Input Voltage – Low	V <sub>IL</sub>	-0.3		V <sub>cc</sub> *0.3	V	
2-Wire Serial Interface Clock Rate				400	kHz	
Power Supply Noise (1kHz to 1MHz, Pk-Pk)				66	mVp-p	
Transmitter (TP1)						
Differential Pk-Pk Input Voltage Tolerance		750			mV	
Pk-Pk AC Common-Mode Voltage Tolerance	Low-Frequency (V <sub>CM<sub>LF</sub></sub> )			32	mV	
	Full-Band (V <sub>CM<sub>FB</sub></sub> )			80	mV	
Differential-Mode to Common-Mode Return Loss	RL <sub>Cd</sub>	802.3ck 120G-2			dB	
Effective Return Loss	ERL	8.5			dB	
Differential Termination Mismatch				10	%	
Single-Ended Voltage Tolerance Range		-0.4		3.3	V	
DC Common-Mode Voltage Tolerance		-0.35		2.85	V	
Receiver (TP4)						
Pk-Pk AC Common-Mode Voltage	Low-Frequency (V <sub>CM<sub>LF</sub></sub> )			32	mV	
	Full-Band (V <sub>CM<sub>FB</sub></sub> )			80	mV	
Differential Pk-Pk Output Voltage	Short-Mode			600	mV	
	Long-Mode			845	mV	

<b>Eye Height</b>	EH	15			mV	
<b>Vertical Eye Closure</b>	VEC			12	dB	
<b>Common-Mode to Differential-Mode Return Loss</b>	RLDc	802.3ck 120G-1			dB	
<b>Effective Return Loss</b>	ERL	8.5			dB	
<b>Differential Termination Mismatch</b>				10	%	
<b>Transition Time</b>		8.5			ps	
<b>DC Common-Mode Voltage Tolerance</b>		-0.35		2.85	V	

#### Electrical Low-Speed Control and Sense Signal Specifications

Parameter	Symbol	Min.	Max.	Unit	Notes
<b>Module Output SCL and SDA</b>	VOL	0	0.4	V	
<b>Module Input SCL and SDA</b>	VIL	-0.3	Vcc*0.3	V	
	VIH	Vcc*0.7	Vcc+0.5	V	
<b>InitMode, ResetL, and ModSelL</b>	VIL	-0.3	0.8	V	
	VIH	2	Vcc+0.3	V	
<b>IntL</b>	VOL	0	0.4	V	
	VOH	Vcc-0.5	Vcc+0.3	V	

## Optical Characteristics

Parameter	Symbol	Min.	Typ.	Max.	Unit	Notes
<b>Transmitter</b>						
<b>Wavelength</b>	$\lambda_C$	1304.5	1311	1317.5	nm	
<b>Side-Mode Suppression Ratio</b>	SMSR	30			dB	
<b>Average Launch Power Per Lane</b>	$AOP_L$	-3.1		4.0	dBm	1
<b>Outer Optical Modulation Amplitude (OMAouter) Per Lane</b>	<b>TDECQ&lt;1.4dB</b>	OMAouter	-0.1	4.2	dBm	
	<b>1.4dB≤TDECQ≤3.4dB</b>		-1.5 + TDECQ			
<b>Transmitter and Dispersion Eye Closure for PAM4 (TDECQ) Per Lane</b>	TDECQ			3.4	dB	
<b>Transmitter Eye Closure for PAM4 (TECQ) Per Lane</b>	TECQ			3.4	dB	
<b>  TDECQ - TECQ  </b>				2.5	dB	
<b>Over/Under-Shoot</b>				22	%	
<b>Transmitter Power Excursion</b>				2	dBm	
<b>Average Launch Power of Off Transmitter Per Lane</b>	Toff			-15	dBm	
<b>Extinction Ratio</b>	ER	3.5			dB	
<b>Transmitter Transition Time</b>	Tr			17	ps	
<b>RIN<sub>17.1OMA</sub></b>	RIN			-136	dB/Hz	
<b>Optical Return Loss Tolerance</b>	ORLT			17.1	dB	
<b>Transmitter Reflectance</b>	TR			-26	dB	2
<b>Receiver</b>						
<b>Wavelength</b>	$\lambda_C$	1304.5	1311	1317.5	nm	
<b>Damage Threshold Per Lane</b>	$AOP_D$	5			dBm	
<b>Average Receive Power Per Lane</b>	$AOP_R$	-7.1		4	dBm	
<b>Receive Power (OMAouter) Per Lane</b>	$OMA_R$			4.2	dBm	
<b>Receiver Reflectance</b>	RR			-26	dB	
<b>Receiver Sensitivity (OMAouter)</b>	<b>TECQ&lt;1.4dB</b>	SOMA		-4.5	dBm	3
	<b>1.4dB≤TECQ≤3.4dB</b>			-5.9 + TECQ		
<b>Stressed Receiver Sensitivity (OMAouter) Per Lane</b>	SRS			-2.5	dBm	4
<b>Conditions of Stressed Receiver Sensitivity Test</b>						
<b>Stressed Eye Closure for PAM4 (SECQ) Per Lane Under Test</b>	SECQ		3.4		dB	

### Notes:


1. Average launch power, per lane (minimum), is informative and not the principal indicator of signal strength.
2. Transmitter reflectance is defined looking into the transmitter.
3. Receiver sensitivity (OMAouter) per lane (maximum) is informative and is defined for a transmitter with a value of SECQ up to 3.4dB.
4. Measured with conformance test signal at TP3 for the  $BER = 2.4 \times 10^{-4}$ .

## Pin Descriptions


Pin	Logic	Symbol	Name/Description	Notes
1		GND	Module Ground.	
2	CML-I	Tx2+	Transmitter Non-Inverted Data.	
3	CML-I	Tx2-	Transmitter Inverted Data.	
4		GND	Module Ground.	
5	CML-I	Tx4+	Transmitter Non-Inverted Data.	
6	CML-I	Tx4-	Transmitter Inverted Data.	
7		GND	Module Ground.	
8	CML-I	Tx6+	Transmitter Non-Inverted Data.	
9	CML-I	Tx6-	Transmitter Inverted Data.	
10		GND	Module Ground.	
11	CML-I	Tx8+	Transmitter Non-Inverted Data.	
12	CML-I	Tx8-	Transmitter Inverted Data.	
13		GND	Module Ground.	
14	LVCMSO-I/O	SCL	2-Wire Serial Interface Clock.	
15		Vcc	+3.3V Power Supply.	
16		Vcc	+3.3V Power Supply.	
17	Multi-Level	LPWn/PRSn	Low-Power Mode/Module Present.	
18		GND	Module Ground.	
19	CML-O	Rx7-	Receiver Inverted Data.	
20	CML-O	Rx7+	Receiver Non-Inverted Data.	
21		GND	Module Ground.	
22	CML-O	Rx5-	Receiver Inverted Data.	
23	CML-O	Rx5+	Receiver Non-Inverted Data.	
24		GND	Module Ground.	
25	CML-O	Rx3-	Receiver Inverted Data.	
26	CML-O	Rx3+	Receiver Non-Inverted Data.	
27		GND	Module Ground.	
28	CML-O	Rx1-	Receiver Inverted Data.	
29	CML-O	Rx1+	Receiver Non-Inverted Data.	
30		GND	Module Ground.	
31		GND	Module Ground.	
32	CML-O	Rx2+	Receiver Non-Inverted Data.	
33	CML-O	Rx2-	Receiver Inverted Data.	
34		GND	Module Ground.	
35	CML-O	Rx4+	Receiver Non-Inverted Data.	
36	CML-O	Rx4-	Receiver Inverted Data.	

<b>37</b>		GND	Module Ground.	
<b>38</b>	CML-O	Rx6+	Receiver Non-Inverted Data.	
<b>39</b>	CML-O	Rx6-	Receiver Inverted Data.	
<b>40</b>		GND	Module Ground.	
<b>41</b>	CML-O	Rx8+	Receiver Non-Inverted Data.	
<b>42</b>	CML-O	Rx8-	Receiver Inverted Data.	
<b>43</b>		GND	Module Ground.	
<b>44</b>	Multi-Level	INT/RSTn	Module Input/Module Reset.	
<b>45</b>		Vcc	+3.3V Power Supply.	
<b>46</b>		Vcc	+3.3V Power Supply.	
<b>47</b>	LVCMOS-I/O	SDA	2-Wire Serial Interface Data.	
<b>48</b>		GND	Module Ground.	
<b>49</b>	CML-I	Tx7-	Transmitter Inverted Data.	
<b>50</b>	CML-I	Tx7+	Transmitter Non-Inverted Data.	
<b>51</b>		GND	Module Ground.	
<b>52</b>	CML-I	Tx5-	Transmitter Inverted Data.	
<b>53</b>	CML-I	Tx5+	Transmitter Non-Inverted Data.	
<b>54</b>		GND	Module Ground.	
<b>55</b>	CML-I	Tx3-	Transmitter Inverted Data.	
<b>56</b>	CML-I	Tx3+	Transmitter Non-Inverted Data.	
<b>57</b>		GND	Module Ground.	
<b>58</b>	CML-I	Tx1-	Transmitter Inverted Data.	
<b>59</b>	CML-I	Tx1+	Transmitter Non-Inverted Data.	
<b>60</b>		GND	Module Ground.	


## Electrical Pad Layout



## Recommended OSFP Host Board Schematic



## Mechanical Specifications



## About ProLabs

Our experience comes as standard; for over 15 years ProLabs has delivered optical connectivity solutions that give our customers freedom and choice through our ability to provide seamless interoperability. At the heart of our company is the ability to provide state-of-the-art optical transport and connectivity solutions that are compatible with over 90 optical switching and transport platforms.

## Complete Portfolio of Network Solutions

ProLabs is focused on innovations in optical transport and connectivity. The combination of our knowledge of optics and networking equipment enables ProLabs to be your single source for optical transport and connectivity solutions from 100Mb to 400G while providing innovative solutions that increase network efficiency. We provide the optical connectivity expertise that is compatible with and enhances your switching and transport equipment.

## Trusted Partner

Customer service is our number one value. ProLabs has invested in people, labs and manufacturing capacity to ensure that you get immediate answers to your questions and compatible product when needed. With Engineering and Manufacturing offices in the U.K. and U.S. augmented by field offices throughout the U.S., U.K. and Asia, ProLabs is able to be our customers best advocate 24 hours a day.



## Contact Information

### ProLabs US

Email: [sales@prolabs.com](mailto:sales@prolabs.com)

Telephone: 952-852-0252

### ProLabs UK

Email: [salessupport@prolabs.com](mailto:salessupport@prolabs.com)

Telephone: +44 1285 719 600